



PORTABLE DC-AC INVERTERS

Mains power (230Vac / 50 Hz) from your car battery via the cigarette lighter socket. The ideal portable range of inverters for mains power anywhere.

You know the ritual: You're in the middle of a long trip, be it business or with the family. The cell phone battery or laptop computer battery dies, the children are restless and want to play computer games, and the saga goes on. If there were only a way to have mains power. Well here it is.

The perfect means for charging the battery of your cell phone, portable computer, shaver, TV, or virtually any device while travelling.

The inverters feature:

- Compact Size, Light Weight, High Efficiency
- Low Battery Alarm
- Low Battery Auto Shut-Down
- Overload Protection
- Input Polarity Protection
- High Surge Current Capability

Model	APLM-80-CIG	APLM-80	APLM-100	APLM-150
Input Voltage (Battery)	12 Vdc	12 Vdc or 24 Vdc	12 Vdc or 24 Vdc	12 Vdc or 24 Vdc
Output Voltage	230 Vac	230 Vac	230 Vac	230 Vac
Continuous Power	80 Watt	80 Watt	100 Watt	150 Watt
Peak Power	150 Watt	150 Watt	200 Watt	300 Watt
Output Frequency	50 Hz	50 Hz	50 Hz	50 Hz
Output Waveform	Modified Sinewave	Modified Sinewave	Modified Sinewave	Modified Sinewave
No Load Current Consump.	0.1 A	0.1 A	0.1 A	0.2 A
Efficiency	90 %	90 %	90 %	90 %
Fuse	10 A	10 A	15 A	20 A
Weight	0.18 kg	0.28 kg	0.45 kg	0.48
Dimensions (L x W x H) mm	15 x 60 x 35	115 x 60 x 35	135 x 75 x 40	155 x 70 x 40

APLM-80-CIG



APLM-80



APLM-100



APLM-150



The manufacturer reserves the right to change specifications without prior notice.

(APLM range from 80 Watt to 2500 Watt)