



Panasonic Valve Regulated Lead Acid Batteries

(VRLA 6V and 12V)

Panasonic's Valve Regulated Lead Acid Batteries, previously known as "Sealed Lead Acid Batteries" are high quality, robust, rechargeable batteries, designed to provide outstanding performance in withstanding overcharge, deep discharge, vibration and shock. They are of compact design, which saves installation space, while providing full and reliable power. The use of special sealing epoxies, tongue and groove case and cover construction, and long-sealing paths for posts and connectors, assures that the Valve Regulated Lead Acid Batteries will offer exceptional leak resistance, and allows them to be used in any position.

Type Number	Nom. Volts	Rated Capacity (Ah) 20h rate	Use with Power Supplies	Expected Trickle Life (Years)		Dimensions (mm) Battery Case only			Appr. Mass (kg)
	(V)			At 25°C	At 20°C	Length	Width	Height	
LC-SA122R3AU	12	2.3	Main Power Supply	3-5	5	182.0	23.9	61.7	0.64
LC-R064R2P	6	4.2	Main and Standby	3-5	5	70.0	48.0	1.2.0	0.78
LC-R127R2P	12	7.2	Main and Standby	3-5	5	151.0	64.5	94.0	2.47
LC-P127R2P	12	7.2	Standby Power Supply	6	10	151.0	64.5	94.0	2.50
UP-RW1254P1	12	9.0	Standby Power Supply	3-5	5	151.0	64.5	94.0	2.55
LC-R0612P	6	12.0	Main and Standby	3-5	5	151.0	50.0	94.0	1.95
LC-P0612P	6	12.0	Standby Power Supply	6	10	151.0	50.0	94.0	2.00
LC-RA1212	12	12.0	Main and Standby	3-5	5	151.0	101.0	94.0	3.90
LC-RD1217P	12	17.0	Main and Standby	6	10	181.0	76.0	167.0	6.50
LC-X1224P	12	24.0	Standby Power Supply	6	10	165.0	125.0	175.0	9.00
LC-X1228P	12	28.0	Standby Power Supply	6	10	165.0	125.0	175.0	11.0
LC-XC1228AP	12	28.0*	Main and Standby	6	10	165.0	125.0	175.00	11.0
LC-XC1228P	12	28.0	Main and Standby	6	10	165.0	125.0	175.0	11.0
LC-X1238AP	12	38.0	Standby Power Supply	6	10	197.0	165.0	175.0	13.0
LC-X1242AP	12	42.0	Standby Power Supply	6	10	197.0	165.0	175.0	16.0
LC-X1265P	12	65.0	Standby Power Supply	6	10	350.0	166.0	175.0	20.0

* Deep Cycle

The manufacturer reserves the right to change specifications without prior notice.